

Technische daten

Fluke PM8918/301 ScopeMeter Low Pass Filter Probe



Produktübersicht: Fluke PM8918/301 ScopeMeter Low Pass Filter Probe

One (blue) 10:1 probe for low frequency applications. Useful bandwidth is 4 kHz, reducing noise pick-up in noisy environments such as in automotive applications. The design is optimized for user's safety, double insulated according to IEC 1010-2-031 CAT III.

Technische Daten: Fluke PM8918/301 ScopeMeter Low Pass Filter Probe

Specifications	
Probe length	2.5m (8 ft.)
Maximum signal voltage	600V rms. CAT III per IEC 1010-2-031
Maximum voltage to ground	600V rms. CAT III per IEC 1010-2-031
Aenuation	10x

Bandwidth	4 kHz
Input resistance	10 MΩ
Input capacitance	12.5pF
Compensation range	15 to 35 pF
When using the mini Test-hooks any potential must not exceed 42 Vpk / 30 Vrms	

Modelle



Fluke PM8918 301

One (blue) 10:1 probe for low frequency applications. Useful bandwidth is 4 kHz, reducing noise pick-up in noisy environments such as in automotive applications. The design is optimized for user's safety, double insulated according to IEC 1010-2-031 CAT III.

Fluke. *Damit Ihre Welt intakt bleibt.*

Fluke (Switzerland) GmbH

Industrial Division
Hardstrasse 20
CH-8303 Bassersdorf
Telefon: +41 (0) 44 580 7504
E-Mail: info@ch.fluke.nl
www.fluke.ch

©2025 Fluke Corporation. Alle Rechte vorbehalten.
Anderungen vorbehalten
03/2025

**Dieses Dokument darf nicht ohne die schriftliche
Genehmigung der Fluke Corporation geändert
werden.**

Technischer Beratung:

Beratung zu Produkteigenschaften, Spezifikationen,
Messgeräte und Anwendungsfragen
Tel.: +49 (0) 7684 8 00 95 45
E-Mail: techsupport.dach@fluke.com