

**TECHNICAL DATA** 

## Fluke i1010 AC/DC Current Clamp



### **Key features**

- The Fluke i1010 AC/DC current clamp is a battery-powered Hall-effect probe that extend the current ranges of Fluke tools, measuring DC current from 1 A to 1000 A and AC current from 1 A to 600A.
- Provides accurate current reading without breaking the circuit.
- Compatible with most Fluke multimeters.
- CAT III 600 V safety rating

#### **Product overview: Fluke i1010 AC/DC Current Clamp**

Fluke current clamps extend the current ranges of Fluke tools. The Fluke i1010 AC/DC current clamp is highly reliable, measures 1 A to 1000 A and provides accurate current reading without breaking the circuit. This clamp measures both ac and dc current with a large jaw, battery-powered Hall-effect probe that gives access to difficult to reach areas. Compatible with most Fluke multimeters.

#### **Specifications: Fluke i1010 AC/DC Current Clamp**

Specifications	
Measurement type	Hall sensor



Nominal current range	600 A, AC 1000 A, DC
Continuous current range	1 A - 600 A, AC 1 A - 1000 A, DC
Maximum non-desctructive current	1000 A
Lowest measureable current	0.5 A
Basic accuracy	2% + 0.5 A (% reading + floorspec)
Useable frequency	DC - 10 kHz
Output level(s)	1 mV/A
Zero error adjustment	Yes
Safety Specifications	
Safety	CAT III, 600 V
Maximum voltage	600 V
Mechanical and General Specifications	
Warranty	1 year
Baery life	9 V, 60 h
Maximum conductor diameter	30 mm 2 x 25 mm
Output cable length	1.6 m



# **Ordering information**



Fluke i1010

Fluke i1010 AC/DC Current Clamp



#### **Fluke**. Keeping your world up and running.®

Fluke (UK) Ltd.
52 Hurricane Way
Norwich, Norfolk
NR6 6JB
United Kingdom
Tel.: +44 (0)20 7942 0708
E-mail: cs.uk@fluke.com
www.fluke.com/en-gb

©2025 Fluke Corporation. All rights reserved.

Data subject to alteration without notice.

04/2025

Modification of this document is not permitted without written permission from Fluke Corporation.