

TECHNICAL DATA

8508A-LEAD | Comprehensive Measurement Lead Kit



Product overview: 8508A-LEAD | Comprehensive Measurement Lead Kit

The 8508A Reference Multimeter has excellent performance specifications. But stability and accuracy can be compromised by the use of inappropriate connecting leads and associated processes when performing measurements.

For the most demanding and most sensitive measurement applications, the 8508A-LEAD set includes high quality, low leakage, low dielectric absorption PTFE insulated cables, terminated with 6 mm gold plated copper spade terminals. Their insulation properties make them ideal for resistance and current measurements minimizing leakage current and charge storage problems; their low capacitance makes them ideal for ac applications; and the 6 mm gold plated copper spade terminals ensure low thermal emfs for dc voltage and resistance work.

Also included in the 8508A/LEAD set is the 8508A's general purpose lead set. (This general purpose lead set also comes standard with the 8508A.) These leads provide the convenience of making rapid connections for less demanding applications and troubleshooting. This kit includes test leads with various test probes and alligator clips.

8508A-LEAD set contents (Item number 1886203)

| Quantity | Description |
|----------|---|
| 4 | 1.5 m two core screened low thermal cable with 6 mm gold plated copper spade terminals |
| 1 | 1 m screened 322/0.1 copper (30 Amp rating) with 6mm gold plated copper spade terminals |
| 2 | Four-wire shorting PCB. (used to null front and rear input) |
| 2 | Locking adaptor 4 mm binding post to safety |
| 1 | General purpose lead kit and probes |

Ordering information



8508A-LEAD

Comprehensive Measurement Lead Kit

Fluke. *Keeping your world up and running.®*

Fluke (UK) Ltd.
52 Hurricane Way
Norwich, Norfolk
NR6 6JB
United Kingdom
Tel.: +44 (0)20 7942 0708
E-mail: cs.uk@fluke.com
www.fluke.com/en-gb

©2025 Fluke Corporation. All rights reserved.
Data subject to alteration without notice.
03/2025

**Modification of this document is not permitted
without written permission from Fluke
Corporation.**