



i1010 AC/DC



- The Fluke i1010 AC/DC current clamp is a battery-powered Hall-effect probe that extend the current ranges of Fluke tools, measuring DC current from 1 A to 1000 A and AC current from 1 A to 600A.
- Provides accurate current reading without breaking the circuit.
- Compatible with most Fluke multimeters.
- CAT III 600 V safety rating

:i1010 AC/DC

Fluke 1010 AC/DC . Fluke i1010 AC/DC .





:i1010 AC/DC






사양

□ □ □ □ □ □	600A AC 1000A DC
□ □ □ □ □ □	1A~600A, AC 1A~1000A, DC
□ □ □ □ □ □ □	1000A
□ □ □ □ □ □ □ □ □	0.5 A
□ □ □ □ □	2% + 0.5 A (% □ □ □ + floorspec)
□ □ □ □ □ □ □	DC ~ 10 kHz
□ □ □ □	1mV/A
0 □ □ □ □ □	□ □
안전 사양	
□ □	CAT III, 600V
□ □ □ □	600V
기계 및 일반 사양	
□ □	1□
□ □ □ □ □	9V, 60h
□ □ □ □ □ □	30mm 2 x 25 mm
□ □ □ □ □ □ □	1.6m
□ □ □ □ □ □ □ □ □	□ □



Fluke i1010

Fluke i1010 AC/DC Current Clamp



Fluke. *Keeping your world up and running.*[®]

Fluke Corporation
PO Box 9090, Everett, WA 98206 U.S.A.

(주)한국플루크Fluke Korea
Tel.02.539.6311
(주)한국플루크 대구지사
Tel.053.382.6311
www.fluke.co.kr

Fluke Korea
서울특별시 강남구 영동대로 517,10층 1002호
(삼성동, 아셈타워)
©2025 Fluke Corporation.
사양은 예고 없이 변경될 수 있습니다.
04/2025

Fluke Corporation .