

Thông số kỹ thuật

Fluke FTP SureGrip™ Fused Test Probes



Tính năng chính

- Built-in fuses for additional measurement protection
- Probes allow indication of live voltage even with blown fuse, helping to prevent the user from thinking no voltage is present
- 2 mm threaded probe tips include removable 4 mm lantern-style spring contacts and removable GS38 insulated IC caps for probing closely spaced leads
- Operating temperature – 20°C to 50°C (-5°F to 120°F)
- CAT III 1000 V, CAT IV 600 V, 10 A rating

Tổng quan sản phẩm: Fluke FTP SureGrip™ Fused Test Probes

In response to new ESA guidelines, Fluke introduces test probes with built-in fuses for additional measurement protection. And, if the probe fuse does blow, these probes will still allow the meter to indicate live voltage helping to prevent a possible misreading of no voltage present. The new modular FTP probes can mount onto any Fluke modular lead format. Rated to CAT III 1000 V, these probes also have removable sheathed tips for additional safety.

Thông số kỹ thuật: Fluke FTP SureGrip™ Fused Test Probes

- Probes allow indication of live voltage even with blown fuse for added security¹
- Built-in 1000 V, 11 A fuses with 20 kA interrupt rating

- 2 mm threaded probe tips include removable 4 mm lance-style spring contacts and removable GS38 insulated IC caps for probing closely spaced leads
- Operating temperature -20°C to 50°C (-5°F to 120°F)
- CAT III 1000 V, CAT IV 600 V, 10 A rating, Pollution Degree 2
- Recommended for use with Fluke modular TL224 SureGrip™ silicone test leads and compatible with most modular test leads
- Replace fuse by unscrewing probe handle at finger guard. Use only Fluke fuse part number 803293
- Current mode is non-functional with blown fuse

1. Voltage readings with blown fuse are approximate and vary with the meter impedance. Before and after each measurement, verify presence of blown fuse by checking continuity of the fused test probe. See explanation below under “DMM Input Impedance.” Current mode is non-functional with blown fuse.

Model



Fluke FTP

Fluke FTP SureGrip™ Fused Test Probes

Fluke. *Giữ cho thế giới của bạn. không ngừng vận động.*

Fluke Corporation
PO Box 9090, Everett, WA 98206 U.S.A.

For more information call:
In the U.S.A. (800) 443-5853
In Europe/M-East/Africa
+31 (0)40 267 5100
In Canada (905) 890-7600
From other countries +1 (425) 446-5500

Representative office of Fluke South East Asia Pte Ltd

C/O Danaher Vietnam
Green Power Tower, 11th Floor Unit 2
35 Ton Duch Thang Street, District 1
Ho Chi Minh City
Vietnam
Tel: +84-8-2220-5371 (ext 103)
Email: info.asean@fluke.com
www.fluke.com/vn

©2025 Fluke Corporation. Specifications subject to change without notice.
04/2025

Modification of this document is not permitted without written permission from Fluke Corporation.