

Tekniset tiedot

Fluke T5-600 Jännite-, virta- ja jatkuvuustesteri





Tärkeimmät ominaisuudet

- Measure current up to 100 A without breaking the circuit
- Meter automatically selects AC or DC voltage, up to 600 V
- Resistance measurements up to 1000 Ω plus continuity test
- Work in tight spaces with detachable SlimReach™ probe tips

Tuotekatsaus: Fluke T5-600 Jännite-, virta- ja jatkuvuustesteri

The T5-600 Electrical Tester is a versatile troubleshooting tool you can carry to every job site. Use it to check voltage, continuity, and current, all with one compact, rugged tool. Just select volts, ohms, or current and the tester does the rest. For higher voltage applications check out the Fluke T5-1000.

"This meter is perfect for my use as I do HVAC and Electrical work, and this will give me what I need for troubleshooting and performance of equipment." - Paul

Measure current up to 100 A without breaking the circuit with OpenJaw™ design

The trendsetting OpenJaw™ design allows for fast and easy current measurement, safely and without metallic contact to a live conductor. The integrated protection circuit allows it to stay connected to a voltage source longer than a solenoid tester would be able to. The T5-600 is also designed to:

- Withstand a 10 ft. (3 m) drop
- Conserve battery life with auto-off mode
- Fit in one hand with handy probe storage in the back of the holster
- Accept Fluke accessory test clips with the test leads

Meter automatically selects AC or DC voltage for tests up to 600 V

Voltage tests are faster and easier than ever before. Just turn the knob to voltage (V) and place your leads on the test points. The T5-600 auto-selects either AC or DC voltage, depending on what is detected. This meter is suitable for both residential or commercial applications and is designed to keep you safe with a CAT III 600 V rating.


FieldSense Information

Learn how to use the T5:

[Download the Quick Reference Guide](#)

[Download the T5 "How-To" Demonstration Guide](#)

[Read the FieldSense Proving Unit Demonstration Guide](#)



T6 Electrical Tester Helps Team at Cutting Edge Cancer Research Center

Tekniset tiedot: Fluke T5-600 Jännite-, virta- ja jatkuvuustesteri

Specifications	
Jaw opening	12.9 mm (0.5 in)
Max wire size	1/0 THHN Cable
Current range AC rms	0 to 100.0 A
Accuracy AC current (50/60 Hz)	3% ± 3 counts
AC response	Averaging
Voltage range AC/DC	0 to 600 V
Voltage accuracy	AC 1.5% ± 2 counts
	DC 1% ± 1 count
Resistance range	0 to 1000 Ω
Continuity beeper threshold	On at < 25 Ω, off at > 400 Ω
Volts indicator LED threshold	Guaranteed on by 30 V AC
Environmental Specifications	
Operating temperature	-10°C to 50°C
Storage temperature	-30°C to 60°C
Humidity (without condensation)	0% to 95% (5°C to 30°C); 0% to 75% (30°C to 40°C); 0% to 45% (40°C to 50°C)
Dust/water resistance	Yes
Operating altitude	2000 meters max
Temperature coefficient	0.1 x (specified accuracy)/°C (< 18°C or > 28°C)
Safety Specifications	
Measurement Category	IEC 61010-2-032, IEC61010-2-033: CAT III 600 V, 100 A ac
Agency approvals	CSA, TUV
Maximum voltage	600 V between any terminal and earth ground
Mechanical and General Specifications	
Size	30.5 x 51 x 203 mm
Weight	300 g
Warranty	Two-years
Baery life	200 hour zinc chloride, 400 hour alkaline
Baery type	2 x AA
Low baery indicator	Yes
Current sensor opening	12.9 mm

Mallit



Fluke T5-600

600 V:n jännite-, jatkuvuus- ja virtatesteri

Includes:

- 600 V Voltage, continuity and current tester
- 4 mm detachable probes
- Instruction sheet

Optional accessories

H5 Vyölaukku (Fluke T3/T5)

Maastokuvioitu Fluke CAMO-37 -kantolaukku

AC220 SureGrip™ -hauenleuat

ACC-T5-KIT Lisävarustesarja T5-testerille

Description

Kestävä kankainen kotelo, jossa on vyölenkki ja kiinnityspaikka mittajohdoille.

Valitse oikea kantolaukku Fluke-laitteillesi.

SureGrip™-varusteiden kumivalupinnat ja sormille muotoillut paikat antavat käyttäjälle mukavan ja tukevan otteen, jolloin voi keskittyä paremmin tarkkaan mittaukseen.

Special value starter kit for the electrical professional who already owns a Fluke T5 Electrical Tester or is thinking of buying one.

Fluke. *Keeping your world up and running.®*

Fluke Finland Oy
Teknobulevardi 3-5
01530 VANTAA
Puh.: 0800 111 862
E-mail: cs.fi@fluke.com
www.fluke.fi

©2025 Fluke Corporation. Kaikki oikeudet
pidätetään. Oikeudet muutoksiin ilman
ennakkoilmoitusta pidätetään.
04/2025

**Tätä asiakirjaa ei saa muokata ilman Fluke
Corporationin kirjallista lupaa.**