

Teknik veriler

PM9091/001 Koaksiyel BNC kablo seti, renk kodlu, 3 parça, her biri 1,5 m



Temel özellikler

- Kablo uzunluğu 1,5 metredir
- Maksimum Sinyal Voltajı: 300 V rms
- Toprağa göre Maksimum Voltaj: 600 V rms. IEC 61010-2-031 için CAT III
- ScopeMeter 120 Serisi ekranlı banana fiş girişlerine uyması için, BB120 Ekranlı Banana'dan BNC'ye dönüştürme adaptörü gerekir.

Ürün İncelemesi: PM9091/001 Koaksiyel BNC kablo seti, renk kodlu, 3 parça, her biri 1,5 m

Her bir sette, kolay tanımlama için renkli (kırmızı, gri ve siyah) BNC erkek konnektörlü üç adet siyah kablo.

Modeller



Fluke PM9091

50 Ohm Coaxial BNC cable set (3 x 1.5m)

Fluke. *Keeping your world up and running.®*

Fluke TURKIYE
P.O. Box 1186
5602 BD Eindhoven
The Netherlands
www.fluke.com.tr

©2025 Fluke Corporation. All rights reserved.
Data subject to alteration without notice.
04/2025

Mer information:

U.S.A. (800) 443-5853 TR +31 (0)40 267 5100 Canada
(905) 890-7600 Övrigt +1 (425) 446-5500

**Modification of this document is not permitted
without written permission from Fluke Corporation.**