

Teknik veriler

EI-162BN 320 mm Diameter Split Core Transformer



Temel özellikler

External dimensions (LxWxD): 46 x 36 x 16 cm (20.5 x 16 x 17.2 in)

Weight: 8 kg (17.6 lbs)

Ürün İncelemesi: EI-162BN 320 mm Diameter Split Core Transformer

Used as a Selective clamp for ground loop resistance measurement around power pylons. Inner diameter of the clamp is 320 mm (12.6 in). Includes the split core transformer. This Split Core Transformer can be used in conjunction with the 1625 Kit* or the 1623 Kit*.

* If non-kit version is owned, the GEOX Probe Cable must be purchased separately.

External dimensions (LxWxD): 46 cm x 36 cm x 16 cm (20.5 in x 16 in x 17.2 in)

Weight: 8 kg (17.6 lbs)

Modeller



Fluke EI 162BN

320 mm Diameter Split Core Transformer

Fluke. *Keeping your world up and running.®*

Fluke TURKIYE
P.O. Box 1186
5602 BD Eindhoven
The Netherlands
www.fluke.com.tr

©2025 Fluke Corporation. All rights reserved.
Data subject to alteration without notice.
04/2025

Mer information:

U.S.A. (800) 443-5853 TR +31 (0)40 267 5100 Canada
(905) 890-7600 Övrigt +1 (425) 446-5500

**Modification of this document is not permitted
without written permission from Fluke Corporation.**