

技術資料

Fluke 303 電流鉤錶



主要功能

- 全新機身設計，更加小巧美觀，符合大眾期許的產品大小，外觀及手感，讓測量工作變得更靈活簡單。
- 交流電流600A，可與滿足不同應用需求的客戶。
- 30mm的大鉗口。
- CAT IV 300V/CAT III 600V的高安全等級。
- 1.8%的高精確度。
- 背光顯示功能。
- 兩年保固。

產品概述: Fluke 303 電流鉤錶

Fluke303是個結實、小巧交流鉗形表，使用簡單，可以滿足日常基礎電氣維護的需要，並且具有以下特點：交流電流600A，可以滿足不同應用需求的客戶；全新機身設計讓Fluke 303交流鉗形表更加小巧美觀，大眾期許的產品大小、外觀及手感。

規格: Fluke 303 電流鉤錶

技术指标		302+	303
交流電流	範圍	400.0A	600.0A
	準確度	1.8%±5	1.8%±5
交流電壓	範圍	400.0/600	400.0/600
	準確度	1.5%±5	1.5%±5
直流電壓	範圍	400.0/600	400.0/600
	準確度	1.0%±5	1.0%±5
直流毫伏量程			
電阻	範圍	4000Ω	4000Ω
	準確度	1%±5	1%±5
導通性		≤70Ω	≤70Ω
背光顯示		是	是
數據保持功能		是	是
鉗口尺寸	高 x 寬 x 厚(mm)	208 x 58.5 x 28	208 x 58.5 x 28
	鉗口大小	30 mm	30 mm
安全等級		CAT III 600 V	CAT III 600 V
溫度		0 -40°C	0 -40°C
屏幕刷新率		>2次/秒	>2次/秒
測試導線		TL75	TL75



電池	2 節AAA 電池	2 節AAA 電池
質保期	2年	2年

機型



Fluke 303 電流鉤錶

Compact. Easy to use. Fluke tested.

The Fluke 303 comes with all the rugged, reliable and accurate features you have come to trust, in a small, ergonomic design. The innovative body design offers a more compact tool to meet your needs. With features of AC current measurements up to 600 A, a large 30 mm jaw opening and CAT IV 300 V/CAT III 600 V safety rating, you get an easy-to-use tool that handles your everyday electrical maintenance needs.

包括：

- Fluke 303 電流鉤錶
- 2 節 AA 電池（已安裝）
- 使用手冊
- 測試導線
- 2年保固

Fluke. 保持您的世界運作不懈。

Fluke Corporation
PO Box 9090, Everett, WA 98206 U.S.A.

更多資訊
U.S.A. (800) 443-5853
Europe/M-East/Africa
+31 (0)40 267 5100
Canada (800)-36-FLUKE
其他 +1 (425) 446-5500
www.fluke.com/zh-tw

©2025 Fluke Corporation. Specifications subject to
change without notice.
04/2025

Modification of this document is not permitted
without written permission from Fluke Corporation.